

**OBT-8012 PA SYSTEM TEN ZONES SECURITY ALARM
MATRIX CONTROLLER MATRIX FIRE SELECTOR**

Ten Zones Matrix Controller OBT-8012 1 channel background music power amplifier input, 1 channel fire/emergency power amplifier input, 10 channels output, can be arbitrarily choose the output channel. Indicator can judge which channel work, Alarm and paging can be worked while emergency.



1. 2U standard 19 inch industrial chassis, black aluminum oxide wire drawing panel, the handle of humanization, adopt polishing technology, show high-grade temperament.
2. 2 channel amplifier signal input (A road background music, B road emergency/fire amplifier), very district signal output.
3. A way to play background music , B way play emergency/fire signal, B road priority.
4. To trigger a 10-channel alarm output signal cascade to the next station as Fire Matrix.
5. Each partition output power up to 1000W.
6. Microcomputer control, touch buttons, switches or PC signal strobe output partition.
7. Working status indicator to determine the partition.
8. Alarm can be forced strobe.
9. Memory function, power won't lose, utility power is restored automatically strobe.
10. Pass CCC certification.

FEATURES

1 channel background music power amplifier input,
1 channel fire/emergency power amplifier input,
10 channels output, can be arbitrarily choose the output channel.
Indicator can judge which channel work,
Alarm and paging can be worked while emergency.

TECHNICAL PARAMETERS

Model	OBT-8012
Input	100V
Output	100V
Frequency Response	20Hz~20KHz
Relay	DC 24V
Power Consumption	10W
Standby Power Consumption	8W
10 Upper Partition Control Communication Interface	1 Group(25p)
10 Down Partition Control Communication Interface	1 Group(25p)
Circuit Signal Output Interface	2 Groups 6.35
Weight	7Kg
Dimensions	545×525×170mm